

The power of a star in your hand ...

A stylized yellow graphic consisting of two curved lines that meet at the top and sweep downwards, resembling a flame or a stylized 'T'.

Tiablo[®]
A7G R5

User Guide

EDC and Tactical LED Flashlight

AG Series

Specifications

LED: CREE XP-G R5 Lifetime 50 000 Hours
Max Output: 285 Lumens
Reflector: SMO Reflector
Circuit: High efficiency DC-DC regulator
Lens: Toughened ultra clear glass with AR coating
Body: Hard Anodized Type III T6061 Aluminum Alloy
Colour: Black

Remarks

1. Battery anode towards LED to prevent failure.
2. Use the correct battery type as per instructions.
3. Storage of flashlight, keep the housing dry and remove the battery.
4. Damage can occur if inside surface of the reflector is touched.
5. Disassembly, modification, or misuse will void the warranty.

The power of a star in your hand ...

Battery: Two CR123 batteries or
one 18650 Li-ion Battery
Working Voltage: 2.75V to 8.5V
Switch: Tactical / Multifunction Option
Waterproof: IPX-8, beyond 5m depth
Size: Head diameter 32mm, Length 134mm
Candle: For a 25W daylight over a 30 sq.m area,
remove the reflector housing, and stand
on the tail cap.
Weight: 106 grams, excluding battery
Extras: Holster, Lanyard, Spare O-Rings

Multifunction Option

The power of a star in your hand ...

Click once on the tail cap button for Mode A, click a second time for Mode B, click third time to turn off.

Mode A: *Unique infinite variable brightness from 1% to 100% to 1%.*

Factory default is 100% brightness. Change brightness by continually pressing on the tail cap button until the desired brightness is visible. During the adjustment, the light will cycle from 100% to 1% to 100% and flicker once at 1%, twice at 50%, and three times at 100% output.

Mode B: *Adjustable variable speed Strobe and SOS*

Factory default 10Hz Strobe.

Enter the Demonstration cycle by pressing the tail cap button for 3 seconds. All features will cycle continuously.

Press the tail cap button once when the desired setting is visible.

Demonstration cycle:

10Hz strobe

SOS

Standby Flicker every 2 seconds at 10% brightness

Infinite Brightness 1% to 100% to 1% without flicker

Strobe 15Hz to 1Hz

Kindly note removing the tail cap will reset use defined program to factory default.

Service

The power of a star in your hand...

Tiablo will replace your flashlight, within 30 days of purchase, if a failure is caused by a manufacturing defect. Replacement will be with same or similar model if discontinued. Proof of purchase from an authorized dealer, or distributor, with the serial number is required.

Tiablo will repair, exchange parts, or replace your flashlight within 12 months of the purchase date, should a failure occur from normal use. If a problem develops outside of the warranty coverage, Tiablo will repair, supply parts, or replace for a fee, plus shipping cost.

Contact Tiablo, or your local distributor for details.



L.B.141, Laprairie, Quebec J5R 3Y2 Canada

North America Toll Free: 1-866-457-7375

E-mail : info@tiablolight.com

TiabloLight.com